

# Schedule Record

Settings---Record Management ---Choose Channel---Enable plan record---Select record time--  
--Select record save path---Save

IP Camera Client-v2.0.4.6

IP CAMERA

192.168.2.108:80

Channel 01

Select the channel

Enable the plan of record

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23
SUN																								
MON																								
TUE																								
WED																								
THU																								
FRI																								
SAT																								

Copy to all

Disk	Total size(GB)	Available size...	Path
<input type="checkbox"/> C:\	100.000	74.586	C:\MediaRecord\
<input checked="" type="checkbox"/> D:\	416.000	408.017	D:\MediaRecord\
<input type="checkbox"/> E:\	415.508	415.062	E:\MediaRecord\

General Record Length: 5 Min

Alarm Duration Time: 10 Sec

Switch Interval: 10 Sec

Pre-recorded alarm Length: 5 Sec

The remaining disk begins recovery control: 10 GB

Record Format: 264 ← Select the video format

No hard disk space coverage: Yes

Video stream type: Main Stream (Video stream type only in dual stream mode to take e

Save

VERSION: v2.0.4.6

Note:

- 1, If you have more than 1 camera, you can copy record plan to all cameras.
- 2, You can select record save path but can not change saving record to different path.
- 3, You can setup save record to H.264 or AVI format.



# Playback Record

Playback---Select Channel---Select Date---Select Time

The screenshot displays the IP Camera Client software interface. The top bar includes the title 'IP CAMERA', a user profile 'Users: admin', and the date '2017-03-15 18:08:05'. A toolbar contains various icons, with the play button highlighted by a red box. The main area shows a video playback window for 'Local Playback [Channel 01]' displaying a camera view of a white object. On the left, a sidebar shows 'Channel 01' selected. At the bottom, a calendar for '2017/03' is visible, with the 15th highlighted. Below the calendar is a timeline for 'Channel 01', 'Channel 02', and 'Channel 03', with a red box highlighting a recording period between 14:00 and 18:00 on the 15th.

SUN	MON	TUE	WED	THU	FRI	SAT
			01	02	03	04
05	06	07	08	09	10	11
12	13	14	15	16	17	18
19	20	21	22	23	24	25
26	27	28	29	30	31	

Note: PC client software does support playback 4 channels record the same time.